


ACT-580T 5 GHz Digital Bodypack Transmitter

Features

- Newly designed compact and lightweight housing for easy to wear.
- The panel integrates a power switch and a backlit LCD to display all operating information.
- On top of the housing is equipped with an antenna, mute button and mini XLR connector. The Mini XLR audio input connector accepts either a screw-lock or a TA4F quick-lock plug. A remote-control mute jack is for easy activation of the mute function.
- The audio input can match up low and high input impedance. The high dynamic range audio input prevents saturation distortion.
- The world's first ACT™ function provides precise and rapid frequency sync to the receiver.
- The patented battery compartment can be inserted with two AA-type batteries or one rechargeable battery, charging via USB Type-C with the foolproof and safe charging circuit.
- A belt clip for easy wearing.



Specifications

Frequency Range	ISM 5.8 GHz (5,725~5,850 MHz)
RF Power Output	20 mW (country dependent)
Mic Capsule	Paired lavalier mic MU-55L or optional other MIPRO's lavalier and headworn mic capsule modules.
Max. Audio Input	6.5 dBV
Display	Green backlit LCD
Battery	One 18500 lithium-ion battery or two AA alkaline
Charging Type	USB Type-C with the foolproof and safe charging circuit.
Dimensions	63 × 80 × 25 mm (W×H×D)
Weight	Approx. 82 g
Note	Refer to the actual product in the event of product discrepancy.