

C2N-SDC-DC

Shade and Drape Controller, 24V DC

The C2N-SDC-DC is a 2-channel Shade and Drape Controller designed to provide a convenient and cost-effective solution for controlling 24 Volt DC motorized shades and drapes. The C2N-SDC-DC is a Cresnet® device with two independently controlled 24V DC outputs, each designed to provide standard up/down or open/close control of a conventional two-wire bidirectional type motor.

The C2N-SDC-DC mounts in the wall or ceiling using an off-the-shelf 4" square or 2-gang electrical box. Pushbuttons on the front of the unit allow for manual operation of the motors during installation and setup.

SPECIFICATIONS

Load Ratings

Motor Control Channels: 2
Per Channel: 30 Watts (1.25 Amps) @ 24 Volts DC
Total: 30 Watts (1.25 Amps) @ 24 Volts DC
Load Type: 2-Wire 24V DC bidirectional motors, Somfy® LT28B or similar

Power Requirements

Cresnet Power Usage: Up to 33 Watts (1.38 Amps @ 24 Volts DC) depending on motor load, dedicated power supply recommended

Connections – Front Panel

AB 1 – 2: (2) 2-pin 3.5mm detachable terminal blocks providing (2) 24V DC 2-wire bidirectional motor control outputs
NET: (1) 4-pin 3.5mm detachable terminal block; Cresnet slave port, connects to Cresnet control network

Buttons

1 UP/DOWN: (2) buttons for local control of output #1
2 UP/DOWN: (2) buttons for local control of output #2
SETUP: (1) button used for touch-settable ID (TSID)

LED Indicators

PWR: (green) Indicates DC power supplied from Cresnet network
NET: (yellow) Indicates communication with the Cresnet system
SETUP: (red) used for touch-settable ID (TSID)

Environmental

Temperature: 41° to 122°F (5° to 50°C)
Humidity: 10% to 90% RH (non-condensing)

Enclosure

Flat metal plate mountable in a 4-inch square or 2-gang electrical box, 1.5 inch minimum depth



Dimensions

Height: 4.10 in (104.2 mm)
Width: 4.10 in (104.2 mm)
Depth: 1.16 in (29.5 mm)

Weight

0.55 lb (0.25 kg)

MODELS & ACCESSORIES

Available Models

C2N-SDC-DC: Shade and Drapery Controller, 2 outputs for 24 VDC 2-wire bidirectional motors

Available Accessories

CRESNET-HP-NP: Cresnet® “High-Power” Control Cable, non-plenum
CRESNET-NP: Cresnet® Control Cable, non-plenum
CRESNET-P: Cresnet® Control Cable, plenum

Notes:

This product may be purchased from an authorized Crestron dealer. To find a dealer, please contact the Crestron sales representative for your area. A list of sales representatives is available online at www.crestron.com/salesreps or by calling 800-237-2041.

Specifications subject to change without notice. Crestron is not responsible for errors in typography or photography.

Crestron, the Crestron logo, and Cresnet are trademarks or registered trademarks of Crestron Electronics, Inc. in the United States and other countries. Somfy is a trademark or registered trademark of Somfy Systems Inc. in the United States and other countries. Other trademarks and trade names may be used in this document to refer to either the entities claiming the marks and names or their products. Crestron disclaims any proprietary interest in the marks and names of others. ©2012 Crestron Electronics, Inc.

C2N-SDC-DC Shade and Drap​e Controller, 24V DC

CAD DRAWINGS

